

CONTROL PANELS


JA-103K

The JA-103K control panels offer wider possibilities for smart functions and home automation even for small and medium-size buildings. JA-103K control panels are programmed by an updated F-Link that brings together with its firmware new functions like maintenance mode or day/night mode that allows the system to react to the day&night time widely known as an astronomical calendar.

The control panels have in-built LAN communicators for communication with users or surveillance and alarm receiving centres. A memory card is included and is used to store events, voice messages and pictures. Control panels are configured using updated F-Link software.



Product code	JA-103K
Product name	Control panel with LAN communicator
Dimensions	268 x 225 x 83 mm
Number of sections	8
Number of users	50
Number of peripherals	50
Calendar events	20
Number of programmable outputs	32
Number of reports per user	8
Number of configurable ARCs	4
Number of bus terminal boards	1
Communicators	built-in LAN; GPRS/GSM can be purchased as the JA-192Y module
Radio module	NO
Power supply	110 - 230 V / 50 - 60 Hz
Backup battery	1x SA214-2,6 - battery is not included in the product package
Backup bus supply	for 2.6 Ah battery for 12 hours at maximum of 88 mA with active LAN communicator
Note	-



JA-103KRY

Control panel with LAN, GSM and radio module

268 x 225 x 83 mm

8

50

50

20

32

8

4

1

built-in LAN; GSM/GPRS is included as the module JA-192Y

YES

110 - 230 V / 50 - 60 Hz

1x SA214-2,6 - battery is not included in the product package

for 2,6 Ah battery for 12 hours at maximum of 80 mA with active LAN communicator

JA-111R radio module is included.

